

eyeSpy247

Stop Worrying. Start Seeing.

This document details the most efficient way to set up your EyeSpy247 camera for business hours and out of hours services.

During business hours the EyeSpy247 system will regularly record images to your account and out of hours it will go into motion detect mode and record images upon movement and email and/or SMS you at the same time.

Step 1:

Login to your EyeSpy247 account and go to Schedule Captures. Under 'Images' set up a schedule for each of your cameras for weekdays and/or weekends, depending on when you are open for business.

For example, if you are open from 9am to 7pm Monday to Friday and you want to record an image every 20 seconds simply set the start and end times (i.e. 09:00 and 19:00) and enter 1800 in the box next to 'I want to capture'. Click Set when done.

Images

Weekdays | I want to capture images between and

| I want to capture images between and

Weekends | I want to capture images between and

| I want to capture images between and

Step 2:

Go to Media Management. Check the 'Enable all motion captures' box as well as 'Enable SMS' and 'Enable email' as appropriate depending on how you want to be alerted out of hours.

All Captures

There are no captures for this time. Use the box below to search for another date or time.

Enable all motion captures Enable sms Enable email

Step 3:

Now, login to your camera's web interface and go to Event Trigger.

Under New Schedule select the day(s) you want to set up the event time frame for.

If we continue the example above, to record and send motion detect alerts out of hours every day you should set up two schedules as follows:

One with a start time of 19:01 and end time of 24:00 and another with a start time of 00:01 and end time of 08:59. Once you have added the two schedules remember to click Save at the bottom of the page.

NB: Ensure that Motion Detection is ticked next to Trigger Event.

The screenshot shows the 'Event Trigger' configuration page for an EyeSpy247 Network Camera. The page has a light blue background and a navigation menu on the left. The main content area is divided into three sections: 'Event Schedule', 'New Schedule', and 'Trigger Event'.

- Event Schedule:** A text area containing two entries: 'Every day 19:01,24:00' and 'Every day 00:01,08:59'. Below this is a 'Delete' button.
- New Schedule:** A form with the following fields:
 - Effective Time Frame: 'Every day' (dropdown)
 - Start Time: '00' : '01' (hh:mm)
 - End Time: '08' : '59' (hh:mm)
 - 'Add' and 'Clear' buttons
- Trigger Event:** A form with the following fields:
 - Motion Detection
 - Interval: '0' Minute(s) before detecting the next event.
 - Action(s): E-Mail, FTP, HTTP
 - Attachment Type: 'JPEG Image' (dropdown)
 - Frame Rate: '5' fps
 - Pre-Capture Length: '2' Second(s)
 - Post-Capture Length: '1' Second(s)

Summary:

Follow and apply the above 3 steps to set up scheduled recording during office hours and to automatically record and get alerted of motion detect events out of hours.